

TSL-H - S2 - SAMSUNG 98QN90A

TELESCOPIC SCREEN LIFT HEAVY - SIZE 2

future automation


DOWN





Mechanism
as supplied.

UP



UK +44 (0) 1438 833577 **US** +1 (603) 742 9181
www.**FUTUREAUTOMATION**.NET

TECHNICAL SHEET
ISSUE 001
SHEET 1

TSL-H - S2 - SAMSUNG 98QN90A
TELESCOPIC SCREEN LIFT HEAVY - SIZE 2


future automation

SPECIFICATION	MEASUREMENTS
Product Dimensions (WxHxD)	1570mm (61 13/16") x 1289mm (50 3/4") x 201mm (7 16/15")
Maximum Weight Capacity	110Kg (242lbs) - Screen 70Kg (154lbs) + Enclosure 40Kg (88lbs)
Product Weight	100Kg (220.5lb)
Movement Type	Motorised
Power Supply Required	110V - 240V AC
Power Consumption Max.	120W
Power Consumption Standby	3W
Mounting Patterns Supported	VESA 400, 600 W x 400, 600 H
Control Options	IR Remote, RS232, Contact Closure
Product Options / Features	Specific B&O and Loewe mounts / adapters, Custom RAL paint finishes, Marine Outdoor suitable version
Package Contents	Mechanism, IR remote control
Marine Suitable	Yes

TSL-H - S2 - SAMSUNG 98QN90A
TELESCOPIC SCREEN LIFT HEAVY - SIZE 2

future automation


GENERAL INFORMATION



Front access is required to install the lift.


Allow 25mm in front of the screen if the mechanism is to be partially sunk below floor level.


The lid must be easily removed if the mechanism was stuck in the down position. The fixings for the screen are at the top here so it can then be lifted off. The drive to the motor can also be disconnected here allowing the screen and mechanism to be manually lifted.



TRIM PANEL - Not supplied. This trim panel is lifted up as the screen is lowered into the cabinet. Brackets are supplied to attach it.

Key hole details allow the enclosure to be hooked into place.





UK +44 (0) 1438 833577 **US** +1 (603) 742 9181
www.**FUTUREAUTOMATION**.NET


TECHNICAL SHEET
ISSUE 001
SHEET 3


TSL-H - S2 - SAMSUNG 98QN90A
TELESCOPIC SCREEN LIFT HEAVY - SIZE 2

future automation


DOWN POSITION DETAILS

All sizing calculations are based off a 20mm [13/16"] screen enclosure panel thickness. Any increace in this thickness will increace the required space.






DETAIL D



SECTION C-C



SECTION B-B

UK +44 (0) 1438 833577 **US** +1 (603) 742 9181
www.**FUTUREAUTOMATION**.NET


TECHNICAL SHEET
ISSUE 001
SHEET 4


TSL-H - S2 - SAMSUNG 98QN90A


TELESCOPIC SCREEN LIFT HEAVY - SIZE 2

future automation


UP POSITION DETAILS








SECTION E-E



DETAIL F



UK +44 (0) 1438 833577 **US** +1 (603) 742 9181
www.**FUTUREAUTOMATION**.NET


TECHNICAL SHEET
ISSUE 001
SHEET 5

TSL-H - S2 - SAMSUNG 98QN90A
TELESCOPIC SCREEN LIFT HEAVY - SIZE 2


future automation

ENCLOSURE DETAILS


ENCLOSURE LID



ENCLOSURE




DETAIL G




G

IMPORTANT
The Enclosure, Lid, Trim panel and Screen must weigh no more than 100Kg.



TRIM PANEL



SEE CAD FOR FINER DETAIL

UK +44 (0) 1438 833577 **US** +1 (603) 742 9181
www.**FUTUREAUTOMATION**.NET


TECHNICAL SHEET
ISSUE 001
SHEET 6

TSL-H - S2 - SAMSUNG 98QN90A
TELESCOPIC SCREEN LIFT HEAVY - SIZE 2

future automation

INSTALL INSTRUCTIONS

- Check that the cabinet, enclosure, lid and the trim panel are made to the details shown on the previous pages.
- You can stand the mechanism up on its base to test it before putting in the cabinet. See control document for details. Use the IR remote with caution and always cover the STOP button in case of issues. See control document.
- Centrally fix the mechanism to the back of the cabinet in the places shown.
- Run up and down and then add the enclosure.
- Adjust the position of the enclosure and adjust the up and down switches with caution. Temporarily add lid to check height.
- Run screen cables up into enclosure. Secure cables as they enter and leave the cable tracks with cable ties. Make sure no cables can get tangled or caught as the mechanism moves.
- Add trim panel. And adjust so it does not clash in the up or down positions. Watch as it initially moves and cover the STOP button.
- The uprights can be removed from the mechanism and added to the screen at the correct height. Rest screen on floor to connect cables before hooking into place.
- Check movement with screen with caution.
- Adjust switches with caution. Check in the control box to make sure the switches are acting correctly. CC2 LED for up position and CC1 LED for down. They go off when hit.



UK +44 (0) 1438 833577 **US** +1 (603) 742 9181
www.**FUTUREAUTOMATION**.NET

TECHNICAL SHEET
ISSUE 001
SHEET 7